Energy Head with Broadband Coating

ES145C



Description

The ES145C pyroelectric sensor permits direct transformation of radiation energy pulses into voltage pulsess independent of the wavelength of the incident radiation. The ES145C sensor head is built strictly on a coaxial basis and is therefore extremely insensitive to interference from electromagnetic radiation as emitted from a pulsed gas laser.

The ES145C has an aperture diameter of 45 mm. For best performance it is recommended to choose a sensor with an area slightly larger than the beam's cross section. The active sensor area is coated with a black absorber layer which possesses an almost constant absorption in the wavelength range from 185 nm to 25 µm. An EPROM located in the BNC to DE-9 mating adapter stores the spectral response calibration parameter required to provide an accurate energy reading.


The ES145C housing includes an 8-32 threaded mounting hole to accommodate posts and post holders. For electrical insulation of the sensor, a metric and an imperial post adapter is included.


The ES145C can directly connect to an oscilloscope with 1 MΩ input resistance via the BNC connector. To accommodate higher repetition rates, the load resistance can be reduced.


Specifications

Technical Specifications	
Energy Range	500 µJ - 2 J
Resolution	1 µJ
Wavelength Range	185 nm - 25 µm
Max. Repetition Rate (@ 1 MΩ Load Resistor)	30 Hz
Application	Energy Measurement from Short Pulsed Lasers with Pulse Length from sub-ns up to ms
Detector Type	Pyroelectric Sensor
Coating	Black Broadband
Detector Size (Active Area)	Ø45 mm (1.77")
Distance from Front Face to Detector	2 mm (0.08")
Measurement Uncertainty	+/- 5% @ 185 nm - 25 µm
Linearity	+/- 1%
Max. Average Power	0.5 W
Max. Power Density	8 MW/cm² (10 ns Pulse)
Max. Pulse Energy Density	0.15 J/cm²
Thermal Time Constant	20 ms
Cooling	Convection
Sensor Dimensions	Ø75 x 21 mm²
Connector Cable Length	1.5 m
Connector	BNC Male / DE-9p Male, Adapter Included
Post	#8-32 Mounting Thread, Insulation Adapters for Metric and Imperial Posts Included
Weight	0.32 kg
Compatible Consoles	PM100D, PM400, PM320E
Compatible Interfaces	PM103, PM103A, PM103U, PM100USB


Typical Performance Plots







Drawings



BNC Male / DE-9 Male Adapter



Available Accessories

The ES145C is compatible with the Thorlabs imperial and metric post and post-holder series.

Cleaning and Maintenance

There are no serviceable parts in the ES145C head. The housing may be cleaned by wiping with a soft damp cloth. The sensor on the pyroelectric heads cannot be cleaned. Gently blow off any debris using compressed air. If any scratches of other signs of damage remain on the sensor area, contact Thorlabs' service department for repair or replacement. If you suspect a problem with your ES145C, please call Thorlabs and an engineer will be happy to assist you.

As long as the sensor has not been exposed to excessive optical power, the calibration should be very stable over long periods of time (well over a year). However, the detector should be calibrated once a year to ensure accuracy.

