Plates for EC2U, EC3U, and EC4U Enclosures



Description

The EC2US, EC3US, and EC4US Enclosure Plates allow a user to replace the mounting brackets of EC2U, EC3U, and EC4US 19" Rack Electronic Enclosures (sold separately), reducing the profile of the enclosures. The plates can be used in conjunction with the ECUF Rubber Feet to convert the EC2U, EC3U, and EC4U into benchtop enclosures.

Installation

The example images shown here demonstrate the installation of an EC2US plate onto an EC2U enclosure. Installing EC3US and EC4US plates onto EC3U and EC4U enclosures, respectively, follows the same procedure.

1. Open the top cover (as described in the EC2U, EC3U, or EC4U spec sheet).
2. With the included 2 mm hex key, loosen the four M3 countersunk screws on the mounting bracket to remove it from the chassis (image below, left).
3. Put the EC2US, EC3US, or EC4US plate onto the same position. Use three of the four M3 screws to secure the plate to the chassis (image below, right).
4. Repeat on the other side.



EC2U Enclosure Without Modification



EC2U Enclosure Converted for Benchtop Use with ECUF Feet and EC2US Plates



Step 2: Removing Mounting Bracket



Step 3: Installing Enclosure Plate